

Push-to-Exit Bar

Installation Manual



Model	Relays	Push Bar Finish
SD-961A-36	2x Momentary dual-contact (NO/NC/COM): 5A@24VAC/VDC	Silver aluminum
SD-961B-36	2x Momentary dual-contact (NO/NC/COM): 5A@24VAC/VDC	Black

The ENFORCER Push-to-Exit Bars are designed to allow exit from inside an area normally locked by an electromagnetic lock, and to disarm or trigger an alarm when the door is opened. Now available with either brushed aluminum or black finish.



- Two built-in non-latching (momentary) dual-contact switches, NO/NC/COM (SPDT): 5A@24VAC/VDC
- Pushing the bar at any point will send a signal to release the lock and/or sound an alarm
- End caps come off and go on in seconds
- For 36" doors (actual length: 34 1/2")
- Designed for easy cutting in field to match width of non-standard-sized doors
- Rugged, heavy-duty construction
- Attractive silver or black aluminum bar with black base and trim
- Mounting hardware included for metal or wood doors
- Includes: Armored Door Cord
- Not weatherproof. Do not mount on exterior surfaces or where exposed to rain.

Parts List

1x Push bar	4x Locking washers	1x Key	4x Small plastic caps
4x Sex bolts	1x Large plastic cap	4x Machine screws	4x Wood screws
1x Armored door cord		1x Manual	

Specifications

	Contacts type	2x NO/NC/COM (SPDT)
Output	Contacts rating	5A@24VAC/VDC
	Duration	Momentary
	Size	For 36" doors but can be cut to fit (actual length: 34 1/2")
Doors	Material	Wood or metal
	Handed	Non-handed, reversible
Operating temperature		32°~120° F (0°~49° C)
	Push bar	Brushed aluminum
Material	Base	Aluminum alloy
	End cap covers	Plastic
Dimensions		34 1/2" x 2 3/4" x 2 3/8" (876x70x61 mm)
Weight		7-lb (3kg)

Overview

Installation

1. Remove the two end-cap covers from the aluminum top. Remove the two screws on each end and pull the end-cap covers off. Slide the aluminum top off.
2. Measure the width of the door using inches. For 36" doors, skip to step 3. For narrower doors, you will need to cut the bar.
 - a. Subtract the width of the door in inches (NOT mm or cm) from 36. The remainder tells how much to cut from the push bar.
 - b. Remove the end cap nearest the wire connector from the base unit.
 - c. Cut both the base unit and the aluminum top by the same amount.
 - d. Replace the end cap.
 - e. Double-check the length by holding the push bar and aluminum top against the door.
3. Determine the mounting location.

NOTE: The height at which the push bar is mounted may be subject to local regulations.

- a. In most installations, the end with the wire connector should be on the side of the door near the hinges to make it easier to run the wires to the wall.
- b. The best-looking installation will have the push bar centered on the door, as measured from the left and right. However, before drilling the holes, make sure the door opens and closes properly. If not, it may be necessary to adjust the push bar to the right or left a bit. (This must be checked with the aluminum top and its end caps on.)


4. With a pencil, mark the four bolt or screw holes and the hole for the wires on the door, and lay the push bar aside.

NOTE: If the push bar was cut, make sure the end cap on the base unit is set firmly against the base unit before marking the holes.

5. Drill a $3/8"$ (10mm) hole in the door for the wires. Do not drill all the way through the door.
6. For mounting to hollow doors, using sex nuts, see Fig. 1.
 - a. Drill four 6mm holes on the inside of the door for the machine screws.
 - b. Drill four 9.8mm holes, one for each bolt, on the outside of the door in the same locations as the four 6mm holes.
- NOTE:** It is important that the holes be precisely 9.8mm—no smaller, no larger.
- c. Insert a sex bolt in each of the 9.8mm holes.
- d. Screw the 4 machine screws through the push bar into the sex bolts to fix the push bar on the door.
7. For mounting to wood doors, screw the push bar onto the door using one of the four supplied wood screws.
8. Run wires through the door and connect them to the access control device (see *Wiring*, pg. 4).
9. Replace the two end caps.

NOTE: One of the end caps has a square-head bolt under the round plastic cover. That end cap should be mounted on the end of the push bar away from the wire connector.

Fig. 1




Locking the Bar Closed


Included with the push bar is a miniature key with a square hole. To lock the push bar closed (to allow two-way, uncontrolled access to the protected area), remove the square-head bolt's round cover, push the bar in all the way, and turn the square-head bolt with the key. To release the bar, turn the square-head bolt again.

Wiring

Switch 1




Switch 2



NOTE: For electromagnetic locks (fail-safe), connect for push-to-open (N.C. and COM).

Sample Installation



IMPORTANT: Users and installers of this product are responsible for ensuring that the installation and configuration of this product complies with all national, state, and local laws and codes regarding the use of push bars for access security, including suitability for doors accessed by disabled persons and suitability for fire doors (the push bar is not fire-rated). SECO-LARM will not be held responsible for the use of this product in violation of any current laws or codes.

California Proposition 65 Warning: These products may contain chemicals which are known to the State of California to cause cancer and birth defects or other reproductive harm. For more information, go to www.P65Warnings.ca.gov.

WARRANTY: This SECO-LARM product is warranted against defects in material and workmanship while used in normal service for one (1) year from the date of sale to the original customer. SECO-LARM's obligation is limited to the repair or replacement of any defective part if the unit is returned, transportation prepaid, to SECO-LARM. This Warranty is void if damage is caused by or attributed to acts of God, physical or electrical misuse or abuse, neglect, repair or alteration, improper or abnormal usage, or faulty installation, or if for any other reason SECO-LARM determines that such equipment is not operating properly as a result of causes other than defects in material and workmanship. The sole obligation of SECO-LARM and the purchaser's exclusive remedy, shall be limited to the replacement or repair only, at SECO-LARM's option. In no event shall SECO-LARM be liable for any special, collateral, incidental, or consequential personal or property damage of any kind to the purchaser or anyone else.

NOTICE: The SECO-LARM policy is one of continual development and improvement. For that reason, SECO LARM reserves the right to change specifications without notice. SECO-LARM is also not responsible for misprints. All trademarks are the property of SECO-LARM U.S.A., Inc. or their respective owners. Copyright © 2025 SECO-LARM U.S.A., Inc. All rights reserved.

SECO-LARM® U.S.A., Inc.

16842 Millikan Avenue, Irvine, CA 92606
Phone: (949) 261-2999 | (800) 662-0800

Website: www.seco-larm.com
Email: sales@seco-larm.com